

### 3.2.6 NOTIFY BEFORE CONNECT

- When this option is set to Yes, the system will let the mailbox owner know what voice mailbox was dialed before connecting the call. This option may be used to assign more than one voice mailbox to a single extension. For example, an extension can be assigned with one mailbox for sales calls, and another for personal calls. Each time a phone call is received at that extension, CADENCE will announce the mailbox the call is for prior to connecting the call. This option is only valid in a CADENCE supervised call transfer.
- 1 Dial option code 1454.
  - 2 The current value will be played.
  - 3 To hear the current value press 1, to enter a new value press 2, to hear the range of valid values press 3.
  - 4 Press 2 to enter new value.
  - 5 Press 1 for Yes (active ) or 2 for No (canceled).
  - 6 The value you entered is played back to you.
  - 7 If this is correct press 1, to re enter it press 2, to exit without saving press 3.
  - 8 If the entered value is correct press 1.
  - 9 Press # to exit or hang up.

### 3.2.7 NO CALL PROGRESS

- When this option is activated, it will cause the CADENCE to transfer the call and immediately disconnect itself. It is the responsibility of the station to forward a busy or answered call back to the CADENCE extension.
- 1 Dial option code 1455.
  - 2 The current value will be played.
  - 3 To hear the current value press 1, to enter a new value press 2, to hear the range of valid values press 3.
  - 4 Press 2 to enter new value.
  - 5 Press 1 for Yes (active) or 2 for No (canceled).
  - 6 The value you entered is played back to you.
  - 7 If this is correct press 1, to re enter it press 2, to exit without saving press 3.
  - 8 If the entered value is correct press 1.
  - 9 Press # to exit or hang up.