



ELECTRONICS

## Specialized Applications

**Date:** 05/28/02  
**Product:** SVMi-4 (1.2 or above), SVMi-8  
**NO.:** 2002-001

### **TITLE: Pager Notification**

---

#### PAGER NOTIFICATION

When this function is activated, the SVMi-4 will call a beeper service and notify a pager after each message is left in the voice mailbox.

To set this up, follow these steps:

- 1) Open the appropriate mailbox block.
- 2) Press 'Ctrl + D' twice to get to page 3 of the mailbox block.
- 3) Enable pager notification by changing the 'N' to a 'Y' in 'pager notification is enabled'.
- 4) In the 'Dial:' field enter the pager number. For example 555-1234.
- 5) Place your cursor on the 'station' field and press return.
- 6) Every time the SVM dials a number it uses a station block to obtain dialing rules and instructions. Select the 'Beepers' station block and press return. If you need to create a new block to handle different beeper companies you can also do that here.
- 7) Now lets check the contents of the beeper station block. Place your cursor on the 'Beepers' field that you selected in step 6 and press 'Ctrl + O' to open it.
- 8) The Matching dial strings are only used to select a station block according to a match with the dialed digits. We use these when a station block has not been explicitly defined. Because we have explicitly defined this block by selecting it a station block in the previous mailbox block we do not need to use these matching dial strings.

In actual fact, in the mailbox block we could have left the station block blank and selected this beeper block by putting a matching dial string in one of the matching dial string fields, (e.g. if the pager number to dial was 555 1234, we could enter 5551234 in one of the fields of the beeper block. Or we could enter 555????, in which case any time the SVMi-4 needed to dial out a number beginning with 555 it would use this station block).

- 9) The only two fields we need to be concerned with are the prefix and the suffix. These have been entered for you so there should be nothing to do here. The prefix determines what number the SVM will dial before sending the 555-1234 beeper number. The suffix determines what number the SVM will dial after sending the 555-1234 beeper number.
- 10) The prefix contains '9 , ' . This means dial 9 (9) and wait for one second (,) The one second is to get dial tone.
- 11) The suffix contains '~diW,\$K##'. This means to use in band dialing (~di), wait for answer (W), pause for 1 second (,), dial the key value of the mailbox (\$K), and send ## to terminate the call (##).

NOTE: Sometimes you may want to substitute a fixed timer in place of the 'wait for answer' command. To do this insert multiple 1 second pauses (,) or one or more 4 second pauses (\).

All that remains is for the mailbox owner to enter their own personal pager number.

- From the mailbox main menu press 6 for mailbox administration.
- Press 2 for pager notification.
- 2 options are available to you.

Press 1 to toggle pager notification on and off.

Press 2 to set the destination phone number. (you must have SVMi-4 version 1.1 or later to do this

*If you have any questions about this application please contact Technical Support by phone 1800 737 7008 or by email at [techsupportmiami@sta.samsung.com](mailto:techsupportmiami@sta.samsung.com)*

---