



ELECTRONICS

TECHNICAL BULLETIN

Date: February 5, 2001

NO.: 2001-02

TITLE: SVMi-4 Saving Program Changes

This bulletin addresses the proper method of saving changes made in SVMi-4 programming. The system will NOT permanently save any changes made when exiting using "Ctrl + E". Powering down the system or pressing the reset button will delete any changes made to the SVMi-4 system.

There are two methods available to properly save all changes made:

1. When the SVMi-4 does its daily maintenance, which is at three o'clock am.
2. Programming may also be saved manually via the PC interface. From the main menu, go to "(E) Operating Utilities". Followed by "(D) Exit SVMi-4". The system will prompt you for a password, The password is '0000' which is the system administrator's password. Once this is done, you will see the SVMi-4 shutting down properly (ports then system operating software). When the SVMi-4 finishes the shut down procedure, you will see the DOS prompt. At this point press the reset button to restart the system and all changes made will be kept.

One of the two options must take place to properly store all programming changes. Future versions of the SVMi-4 will include a save application in the system main menu.

If you have any questions about this or any other Technical bulletins please contact Technical support by phone 1800 737 7008 or by email techsupportmiami@sta.samsung.com.
