SVMi-20i Upgrade Procedure

- 1) The SVMi-20i software package does not need to be unzipped.
- Login onto the switch using the latest DM program. System IP needs to be set first in MMC 830.
- 3) Set an IP address and gateway for the SVMi-20i in DM 2.2.17 or MMC 873
- 4) The PC needs to be in the same subnet as the system
- 5) Select Package Update.

In order to upgrade the SVMi-20i's firmware, select 'Package Update' in Util tab of the Device Manager. Then, the following window will pop up.

Card 1 SVMi-20i (C1- S Package Information Card IP Address Current Version Disk Total Disk Used Disk Free	2) n 165.213.89.132 V600 7495084 Kbytes 444048 Kbytes 6676282 Kbytes	Update Information Update File Restart The corresponding firmware's version Select File
		Uplead

6) Select the file to update.

Click [...] and select the file to update. If the file is selected, 'firmware's version' will be displayed in File Information.

Card Package Update Card 1 SVMi-20i (C1 - S2)		
Package InformationCard IP Address165.213.89.132Current VersionV600Disk Total7495084 KbytesDisk Used444048 KbytesDisk Free6676282 Kbytes	Update Information Update File E:\V460\package\vm\110906_DV\svmi20i_V600.PKG Restart The corresponding firmware's version V600 Select File	✓ Select
	Uplo	ad

7) Upload the package.

Click **[Upload]** button to start to upload the file. To apply the uploaded file, the SVMi-20i card will be restarted automatically.

Card 1 SVMi-20i (C1 - S	52)		
Package Informati Card IP Address Current Version Disk Total Disk Used Disk Free	on 165.213.89.132 V600 7495084 Kbytes 443564 Kbytes 6676766 Kbytes	Update Information Update File E:IV460\package\vm\110916_DTL_Pmt_Fixed\svmi] Restar The corresponding firmware's version Update complete.	_ V Select
			Upload

8) Upgrade Completed.