



SVMi-20i Remote Access

**** In this example you will learn how to connect Device Manager to an SVMi 20i remotely ****

This example assumes that the SVMi-20i is behind a firewall/router that only has (1) public IP 12.204.186.99

Step-by-Step Instructions

1. MMC 830 will need to be set IP Type to Public w/Private.

- IP: 192.168.1.10
- Subnet Mask: 255.255.255.0
- Gateway: 192.168.1.1
- Public IP: 12.204.186.99

2. MMC 873 will need to be set IP Type to Public with/Private.

- IP: 192.168.1.11
- Subnet Mask: 255.255.255.0
- Gateway: 192.168.1.1
- Public IP: 12.204.186.99

3. Firewall Considerations

- TCP Port 6001 will need to be forwarded to the private IP address of the voice mail. In this example that is 192.168.1.11
- TCP Port 5090 will need to be forwarded to the private IP address of the MP. In this example that is 192.168.1.10

4. DM Considerations

- When accessing remotely, use the public address in your link-setup. In this example the public address is 12.204.186.99



If you have any questions regarding this notice, please contact Samsung Technical Support via e-mail at BCS.support@samsung.com